# How to Firmware Upgrade



1	Login to your camera's web interface by typing in its IP address or .local address. For example http://ptzoptics.local		
	<b>PROPICS</b>		
	L admin		
	Password		
	Login		
	Having Trouble? Visit the knowledge base for all your troubleshooting needs!		
	https://community.ptzoptics.com/		

#### Once logged in, go to the System Settings page.



## Click the Check Firmware Version button.







You may be prompted to download multiple files. Click "Allow" to download the firmware and changelog files.



You may be prompted to approve the download. Click the Keep button on the changelog to approve the download.



7 Now click the Keep button on the firmware file to approve the download.



6

8 Click the arrow to reveal the Advanced section of System Settings.

袋 System Settings	Admin Password:①				
🖒 Reboot	Guest Name:	guest			
	Guest Password:				
→ 1: Studio	⊗ Cancel	Ø Apply			
→ 2: Low Light	Firmuran Obserk				
→ 3: Outdoor		https://firmu/are.ptzoptics.com/			
	Willions.() -				
	& Cancel	& Apply			
	Restore Default				
	🖸 Menu Reset 🕜				
	Advanced				
					———————————————————————————————————————
-;ਊ Tally Status					
			Q Search	💼 🖬 🚮 📄	😑 🖪 🗳 🤤

# Click the Select File button.

<ul> <li>Menu Reset</li> </ul>
Advanced
Firmware upload Select file from your computer
Ø Apply
Restore Defaults
O Network Reset

**10** Navigate to the Download folder and select the \*.img firmware file.

rk Settings Settings	Open	anc	el	Ø Apply	
Info	$\leftarrow \rightarrow \checkmark \uparrow$	7	∠ > Downloads		
n Settings	Organize • New	folde	er		
Reboot	A Home		Name Today           VX60AS         F51.HL         V0.0.73_24M_20240521.img	Date modified	Type Windows.lsc
io	🛄 Desktop	*			
	🛓 Downloads	*			
Light	Documents	*			
loor	Pictures	*			
	🚺 Videos	*			
	🕖 Music	*			
	🙁 Product Team	*			

**11** Click the Apply button to upload the firmware to the camera.

vanced
mware upload
VX60AS_F51.HI_V0.0.73_24M_20240521.img
S Apply
store Defaults
O Network Reset     O      O

12 In 1 ~ 3 minutes a notification will popup informing you the firmware has been uploaded and will take a few minutes to complete.



**13** After 3 ~ 6 minutes, the firmware upgrade process will be complete. Reload the web interface to reveal the new features.

✓ S ptzoptics.local/#system × +					
← → C ▲ Not secure ptzoptics.local/#system					
Reload this page	IK Kemote Channel Selection				
	Access Settings				
Camera Settings	Admin name:				
▶ Audio & Video					
Streaming Settings					
Profile Settings	Guest Name: ① guest				
<ul> <li>↔ Network Settings</li> </ul>	Guest Password:				

7

## 14 Click here



# 15 Click here

<b>PPPTICS</b>
L admin
Password
Login
Having Trouble? Visit the knowledge base for all your troubleshooting needs!
https://community.ptzoptics.com/

### 16 Click here

<b>OPTICS</b>
L admin
• ••••
Login
Having Trouble? Visit the knowledge base for all your troubleshooting needs!
https://community.ptzoptics.com/

17 Once logged in, press **Shift** + **Ctrl** + **R** to refresh the Web UI without cookies / cache.



#### Click Camera Config.



**19** Check the Device Info page to confirm that your camera has received the new firmware.



20 View the Firmware Version field for the new SOC version.

